



Ortus Recessed Retrofit J-Box Downlight 8"

FEATURES

- Offers up to 80% energy saving in comparison to incandescent/halogen bulbs.
- Designed to fit most 8" cans.
- Switches on instantly.
- Suitable for damp locations.
- Compatible with most dimmers down to 10%.
- Requires no special tools for installation.

PRODUCT DETAILS

LIGHTING PERFORMANCE

Efficacy	70 lm/W	
Power	25 W	30 W
Lumen Output	1750 lm	2100 lm
CCT	3000 K / 4000 K / 5000 K	
CRI	80+	
Voltage	120 V or 277 V, 50 / 60 Hz	
Beam Angle	120°	
Power factor	≥ 0.90	
Dimming	Line Dimmable	

ENVIRONMENT & LIFESPAN

Operating Temperature	-4° F to +113° F
IP Rating	IP40
Operating Hours	50,000 hours
Warranty	5 Years

ORDERING INFORMATION

MODEL	Wattage	CCT
IK-DLR8 -JBOX	0025A-80	3000
	0030A-80	3000 K 4000 K 5000 K

CONSTRUCTION

Housing	Aluminum
Base / Power Supply	Direct Wire / Ballast Bypass
Finish	Architectural White


APPLICATIONS

Ideal for retrofitting inefficient fixtures in residential / commercial ceilings.

QUALIFICATIONS & WARRANTY



DIMENSIONS



Wattage	A(in)	B(in)
25 W - 30 W	7.72	5.52

INSTALLATION

1. Cut the installation hole.
2. Connect the input plug to the socket outlet.
3. Place the LED driver and LED downlight into the ceiling.
4. Ensure all the clearance values are maintained after installation for the LED downlight, LED driver, insulation and any structural members. (see Figure 4, 5 and Clearance Information section)

