TORIN WALL PACK LIGHT



IMPORTANT SAFEGUARDS

PLEASE FIND A QUALIFIED ELECTRICIAN FOR INSTALLATION. Please read the instructions before you install and use the luminaire.

- · To avoid electric shock, disconnect power at source prior to installation.
- The installation should be performed by qualified electricians or lighting technicians.
- Before conducting any installation, maintenance, or removal, disable all power to the luminaries and wait until the fixture cool down.
- Do not touch the fixture while it is in service.
- If there is any problem with the fixture, DO turn off power and DO NOT attempt repair unless you are a qualified technician or the customer service member.
- · Please read the label information carefully to get proper input voltage for this product.
- This luminaire is designed to operate in ambient temperatures ranging from -40° ~ 40°C (-40° ~ 104°F).
- · Suitable for wet locations.
- This product is not available for special environments such as places with corrosive gases or high pressure water vapor.



WARNING DISCONNECT POWER BEFORE INSTALLING OR SERVICING.

1. MOUNTING WITH A 1/2" CONDUIT AT THE BOTTOM


- 1. Loosen two sets of screws and remove the metal template.
- 2. Install EVA gasket on the back of the metal template. (Note the direction of the arrow).
- 3. Pull house supply wires through the hole in the housing back and secure to
- J-Box with two mounting screws.
- 4. Thread the 1/2" conduit into the 1/2" hole.
- 5. Connect Black for Line, White for Neutral and bare wire for Ground to complete the wiring.
- 6. Secure the fixture on the metal template with set screws.

2. MOUNTING WITH J-BOX

- 1. Loosen two sets of screws and remove the metal template.
- 2. Install EVA gasket on the back of the metal template. (Note the direction of the arrow.)
- 3. Pull house supply wires through the hole in the housing back and secure to J-Box with two mounting screws.
- 4. Connect Black for Line, White for Neutral, and bare wire for Ground to complete the wiring.
- 5. Secure the fixture on the metal template with set screws.

PHOTOCELL INSTALLATION

- 1. Install photocell and wires as per diagram.
- 2. Use photocell rated for your supply voltage.



TROUBLESHOOTING

- 1. Check that the line voltage at the fixture is correct. Refer to wiring direction.
- 2. Is the fixture grounded properly?
- 3. Be sure the photocell, if used, is functioning properly.

*©IKIO LED LIGHTING. Unauthorized use or reproduction of illustrations, photographs or text is prohibited. IKIO LED LIGHTING reserves the right to discontinue products or to change the technical and/or design specifications at any time. Email : info@ikioledlighting.com Website : www.ikioledlighting.com Phone : (1) 844-533-4546

